- 1. Запустить MatrixMaker.
- 2. Выбрать File Open. В открывшемся окне выбрать файл с прошивкой. Расширение .dat

ткрыть					?×
Папка:	ST UKMINSTM	IED (D:)	-	🗢 🗈 💣 🔳•	
Недавние документы Рабочий стол Мой документы Мой	1 MSR213V USE 123.dat checkway-s8 checkway-s8	B Driver_20160401 Ob-keyboard-ukm4-rev009.da Ob-keyboard-ukm4-rev009-D3 Ob-keyboard-ukm4-rev00912	it <mark>5.dat</mark> 45.dat		
	Имя файла:	checkway-s80b-keyboard	-ukm4-rev	009-DS.dat 💌	Открыть
Сетевое	Тип файлов:	Binary Files (*.dat)		-	Отмена
окружение		Г Только чтение			

3. Выбрать Keyboard – Update Key Mappings

Retrieve Keyboard 4 Clear Current Layer Clear All			aps Scroll ock Lock	(B)
Keyboard Setting Ber Code Reader Setting MagStripe Card Reader Setting MICR Setting	Ctrl+K Ctrl+B Ctrl+M Ctrl+C			
IButton Setting Update Firmware	Ctrl+I			

Пойдет процесс прошивки раскладки клавиатуры.

<b>580B - checkway-s80b-k</b> File Keyboard Diagnostic La	eyboard-ukm4-rev009-D5.d anguage Help	
Please don't use the l touch the touch panel	7% keyboard, the mouse or !	Num Caps Scroll Look Look Look Look D D D D D D D D D D D D D D D D D D
Dandy	Memory Left: 3066 Bytes	

Перейти к настройкам считывателя.
 Выбрать Keyboard – MagStripe Card Reader Setting

Update Whole Keyboard         Update Key Mappings         Retrieve Keyboard         Clear Current Layer         Clear All         Key Map Preview         Keyboard Setting         Ctrl+K         Bar Code Reader Setting         MagStripe Card Reader Setting         Ctrl+I         Mitcrl Setting         Ctrl+I	
Key Map Preview       Image: Ctrl+K         Keyboard Setting       Ctrl+K         Bar Code Reader Setting       Ctrl+B         MagStripe Card Reader Setting       Ctrl+M         MICR. Setting       Image: Ctrl+I         Button Setting       Ctrl+I	6
Keyboard Setting     Ctrl+K       Bar Code Reader Setting     Ctrl+B       MagStripe Card Reader Setting     Ctrl+M       MICR: Setting     Ctrl+C       Button Setting     Ctrl+I	®
MagStripe Card Reader Setting Ctrl+M MICR Setting Ctrl+C iButton Setting Ctrl+I	
MICR. Setting Ctrl+C Button Setting Ctrl+1	
Update Firmware	
	_

Откроется окно настроек.

Проверить правильность настроек согласно рисунку:

Magstripe Card	Reader Setting			X
Enabled Track 1 🔽 Track 2 🖾 Track 3 🖾	Start Sentinel	End Sentinel		Update OK
✓ Enable     Options     Supp     Supp     Supp     Reve	Beep Read To di pleas Some devices ort IBM card ort OPOS erse reading	ing Sequence: 1-2-3 sable a track in the Reading Sequence, se uncheck the corresponding track. may not be supported> Output data for any valid track Output credit card A/C No. Enable LRC Shown in digital format	Others Header: O ASCII Separator: O ASCII Suffix: O ASCII	<ul> <li>Code</li> <li>Code</li> <li>Code</li> </ul>

В секции Others Header нажать на Code. Проверить значение префикса. Если верно, нажать ОК или установить нужное значение:

ode (Po	r Indee: 00\		-						I	
Mappin	g Sequence			- Special Codes -						
	Code	Value		Delay 0.5 sec:	0003	In Friday				OK
1	F13	68		Europe 1:	0032				-	
2				F13:	0068					Cancel
3				F14:	0069			- Co	mm	n Manni
4				Vol Up:	0708					t+Del
6				Vol Down:	0709				IITAI	(TDEI
7				Imedia Select:	U/UE					
8				Hex Code	TELEVISION I					
9			-	<u>·</u> 0×		Inse	rt			
Esc	F1 F2 F3 F4	F5 F6 F7	RS	F9 F10 F11 F12				US	4	-
20 10 M 10 10	@2 # 3 \$ 4 %s	6 8 7 8	(9	) 0 + = <-E0xSp	PrtSc Scroll	Pause	Num	1	•	. 3
~ 1 1	Internet and the second s	7 7 77 7	0	P ( [ ) ] I \	Ins Home	PgUp	7	8	9	
Tab->	QWER	1 1 0 1						C		- Low and the low of t
Tab-> Caps	Q W E R	G H J	K	L : " · Erder	Del End	PgDn	4	5	6	
Tab-> Caps Shift	Q W E R A S D F Z X C V	G H J B N M	K .	L	Del End	PgDn	4	5	6	Die

В секции Others Suffix нажать на Code. Проверить значение суффикса. Если верно, нажать ОК или установить нужное значение:

Code (Po	is Index: 02)					
Mappin	g Sequence		Special Codes			
	Code	Value	Delay 0.5 sec: 0003	-		ОК
1	F14	69	Europe 2: 0052			Cancel
2 3 4 5 6 7			F13:         0068           F14:         0069           F15:         006A           Vol Up:         0708           Vol Down:         0709           Media Select:         070E	T	Comm Ctrl+A	ion Mapping
89		· ·		Insert		-
	1 @2 H 3 \$ 4 74 5	1 6 8 7 ° 8 ( 0	) 0 . + . C-BkSp PriSc Scroll	Pause Mm		
	QWER	TYUI	0 p ( [ ) ] I \ Ins Home	PgUp 7	8 9	
Tab->		GHIK	L : Enter Del End	PgDn 4	5 6	
Caps	ASDF					
Cups Shift		B N M <	. > . ? / Shife 1	1	2 3	Enter

В окне настройки считывателя нажать Update

Magstripe Card Reader Setting			
Enabled Start Sentinel Track 1 ☑ % Track 2 ☑ ; Track 3 ☑ ;	End Sentinel ? ? ? ? ? ?		Update OK
<ul> <li>✓ Enable Beep</li> <li>Read</li> <li>★ To dipleas</li> <li>Options <some devices<="" li=""> <li>✓ Support IBM card</li> <li>✓ Support OPOS</li> </some></li></ul>	ing Sequence: 1-2-3 sable a track in the Reading Sequence, se uncheck the corresponding track. may not be supported> Output data for any valid track Output credit card A/C No.	Others Header: C ASCII Separator: C ASCII Suffix:	• Code
Reverse reading	☐ Enable LRC ☐ Shown in digital format	CASCII	• Code

Отключить клавиатуру. Установить на кассу.